



Transformátory EI s pojistkou  
pro zabezpečovací zařízení.  
Výkony 20 - 125 VA



Transformatoren EI mit Sicherung  
von 20 - 125 VA



Transformers EI with fuse  
for protection facilities  
Output 20 - 125 VA



| Výkon [VA]<br>Leistung [VA]<br>Output [VA] | Rozměry [mm] |       | Masse [mm] |      |      | Dimension [mm] |       |
|--------------------------------------------|--------------|-------|------------|------|------|----------------|-------|
|                                            | EI           | a     | b          | c    | d    | e              | f     |
| 20                                         | 60/21        | 81,2  | 53,6       | 46,8 | 72,5 | 43,5           | 98,2  |
| 32                                         | 60/30        | 81,2  | 53,6       | 57,3 | 72,5 | 43,5           | 98,2  |
| 50                                         | 66/34        | 87,2  | 58,6       | 60,2 | 77,5 | 47,5           | 104,2 |
| 80                                         | 78/36        | 99,6  | 69         | 68   | 90   | 57,5           | 116,2 |
| 125                                        | 96/35        | 129,5 | 87,2       | 74,6 | 115  | 70             | 140,1 |

